

# FM-7000 OPERATOR'S GUIDE

ITEM		KEYSTROKE
<b>CH16 DISTRESS CALL</b>		<b>CH16</b>
<b>AUTO REVERT WATCH ON CURRENT CH. WITH THE HANDSET ON THE REST.</b>		Hang the handset in the handset rest. (Ch16 is automatically selected.) <b>SHIFT</b> <b>INTL</b> <b>1</b> etc.
<b>CHANNEL SELECTION</b>		(Channel Number) <b>ENT</b> (or rotate channel selector)
<b>CH MODE (INTL/USA/WX) SELECTION</b>		<b>SHIFT</b> <b>INTL</b> <b>1</b> etc.
<b>MEMORY OPERATION</b>	<b>RECALL</b>	<b>RCL</b> (Memory Number) <b>ENT</b>
	<b>STORE</b>	<b>SHIFT</b> <b>STO</b> <b>RCL</b> (Memory Number) <b>ENT</b> (Channel Mode: INTL/USA) <b>ENT</b> (Channel Number) <b>ENT</b>
	<b>DELETE</b>	<b>SHIFT</b> <b>STO</b> <b>RCL</b> (Memory Number) <b>ENT</b> <b>0</b> <b>ENT</b>
<b>DUAL WATCH</b>	desired CH and CH16	(Desired Channel Number) <b>ENT</b> <b>SHIFT</b> <b>DW</b> <b>CH16</b>
	desired CH and guard CH (in U.S. waters)	<b>SHIFT</b> + <b>DW</b> <b>CH16</b> .... (U.S. coast guard channel should be stored in MEMO 0)
<b>SCANNING (Multiple Watch)</b>	<b>START</b>	<b>SHIFT</b> <b>SCAN</b> <b>5</b>
	<b>STOP</b>	Press the PTT switch or any key.
	<b>SETTING SCAN PARAMETERS</b>	<b>SHIFT</b> + <b>SCAN</b> <b>5</b> → <b>HI/LOW</b> → (1~9) <b>ENT</b> <div style="display: flex; justify-content: space-around; margin-top: 10px;"> <div style="text-align: center;">             ↑ Select HOLD or LOCK mode           </div> <div style="text-align: center;">             ↑ Dual watch quantity           </div> </div>

## OPTIONAL FUNCTIONS

These functions require optional devices.  
Check here if the function is available



<b>HAILER</b>	<b>SHIFT</b> <b>HAILER</b> <b>8</b>	
<b>DSC(class-C) INDIVIDUAL CALL</b>	<b>SHIFT</b> <b>ID</b> <b>HI/LOW</b> (Receiving station's ID) <b>ENT</b> <b>SHIFT</b> <b>CALL</b> <b>9</b>	
<b>INTERCOM</b>	<b>SHIFT</b> <b>INTCOM</b> <b>7</b> (2~5) <b>ENT</b>	
<b>BEEP</b>	Continuous beep 2-tone alarm for 5 sec  5 long beeps	When DSC distress call is received. While sending a DSC distress call. (Beep sounds from handset speaker.) When individual call is received.

